

The ECS for the L0 trigger is associated to the PVSS project **L0\_TRIGGER**. It is linked to the L0DU\_CU, TCALO\_DAQ and the **TMU\_A** and **TMU\_C** ECS control nodes. The 3 L0 subsystems can be controlled from the **TRG\_ECS** node of this project .

The ECS for the L0 MUON is associated to PVSS project **L0\_MUON**.

To use the ECS both projects should be running and their nodes should have been started.

### How to start ECS to use the L0 MUON?

- Make sure the PVSS project L0\_MUON is running and the TMU\_A and TMU\_C nodes are running (see below How to start side A or side C control nodes?)
- Start the PVSS project L0\_TRIGGER.
- Start the Device Editor Navigator from the project console.
- In the Device Editor Navigator window select the FSM tab, select the TRG\_ECS, right click on it and select *Start/Restart tree*
- In the Device Editor Navigator window FSM tab, select the TRG\_ECS, right click on it and select *View*, the ECS control window opens. You can navigate down in the components by double clicking on the nodes buttons.
- Take the control of the ECS by left clicking on the TRG\_ECS node lock icon and selecting *Take*.
- In the bottom of the panel select the side(s) you want to use TMU\_A and/or TMU\_C and exclude all the one you dont want to use (most often they are L0DU\_CU and TCALO\_DAQ). Left click on the nodes lock icons and select *Include* or *LockOut*.
- From the top level node TRG\_ECS use the *ALLOCATE* command to get ressources.
- Once the ressources have been allocated you can send the *CONFIGURE* and then *START* or *STOP* or *RESET* commands to drive the L0 MUON in its different possible states.

### How to start side A or side C control nodes?

- Start the PVSS project L0\_MUON.
- Start the Device Editor Navigator from the project console.
- In the Device Editor Navigator window select the FSM tab, select the TMU\_DAQ, right click on it and select *Start/Restart tree*
- If you want to see the nodes states: in the Device Editor Navigator window FSM tab, select the TMU\_DAQ node, right click on it and select *View*, the ECS control window opens. You can navigate down in the components by double clicking on the nodes buttons in this panel or in the corresponding buttons that are also visible in the TRG\_ECS panels.

### How to quickly navigate in the trigger boards state panels?

- Shortcuts have been implemented in all WINDOWS console machines of the control room. Under the directory G:\online\ecs\Shortcuts\TRG use the TMUDAQC\_UI\_FSM shortcut.

-- PierreYvesDuval - 07 May 2008

---

This topic: LHCb > L0MuonHowTouseECS

Topic revision: r1 - 2008-05-07 - PierreYvesDuval



Copyright &© 2008-2021 by the contributing authors. All material on this collaboration platform is the property of the contributing authors.

or Ideas, requests, problems regarding TWiki? use Discourse or Send feedback